

https://answersun.com/download/solutions-manual-of-introduction-to-electric-circuits-by-dorf-svoboda-7th-edition/



Download full file from answersun.com

https://answersun.com/download/solutions-manual-of-introduction-to-electric-circuits-by-dorf-svoboda-7th-edition/



Solution Manual

to accompany

Introduction to Electric Circuits, 6e

By R. C. Dorf and J. A. Svoboda

Download full file from answersun.com

https://answersun.com/download/solutions-manual-of-introduction-to-electric-circuits-by-dorf-svoboda-7th-edition/

Table of Contents

Chapter 1 Electric Circuit Variables

Chapter 2 Circuit Elements

Chapter 3 Resistive Circuits

Chapter 4 Methods of Analysis of Resistive Circuits

Chapter 5 Circuit Theorems

Chapter 6 The Operational Amplifier

Chapter 7 Energy Storage Elements

Chapter 8 The Complete Response of RL and RC Circuits

Chapter 9 The Complete Response of Circuits with Two Energy Storage Elements

Chapter 10 Sinusoidal Steady-State Analysis

Chapter 11 AC Steady-State Power

Chapter 12 Three-Phase Circuits

Chapter 13 Frequency Response

Chapter 14 The Laplace Transform

Chapter 15 Fourier Series and Fourier Transform

Chapter 16 Filter Circuits


Chapter 17 Two-Port and Three-Port Networks

Download full file from answersun.com

https://answersun.com/download/solutions-manual-of-introduction-to-electric-circuits-by-dorf-svoboda-7th-edition/


P5.5-4

Find R_t:



$$R_t = \frac{12(10+2)}{12+(10+2)} = 6\ \Omega$$

Write mesh equations to find v_{oc}:



Mesh equations:

$$12\,i_1 + 10\,i_1 - 6\left(i_2 - i_1\right) = 0$$
$$6\left(i_2 - i_1\right) + 3\,i_2 - 18 = 0$$

$$28\,i_1 = 6\,i_2$$
$$9\,i_2 - 6\,i_1 = 18$$

$$36\,i_1 = 18 \quad \Rightarrow \quad i_1 = \frac{1}{2}\ \text{A}$$

$$i_2 = \frac{14}{3}\left(\frac{1}{2}\right) = \frac{7}{3}\ \text{A}$$


Finally, $\quad v_{oc} = 3\,i_2 + 10\,i_1 = 3\left(\frac{7}{3}\right) + 10\left(\frac{1}{2}\right) = 12\ \text{V}$

(checked using LNAP 8/15/02)

Download full file from answersun.com

https://answersun.com/download/solutions-manual-of-introduction-to-electric-circuits-by-dorf-svoboda-7th-edition/

P6.4-3



The voltages at the input nodes of an ideal op amp are equal so $v_a = -2$ V.

Apply KCL at node *a*:


$$\frac{v_o-(-2)}{8000}+\frac{12-(-2)}{4000}=0 \quad \Rightarrow v_o=-30 \text{ V}$$

Apply Ohm's law to the 8 kΩ resistor

$$i_o=\frac{-2-v_o}{8000}=3.5 \text{ mA}$$

(checked using LNAP 8/16/02)

P6.4-4



The voltages at the input nodes of an ideal op amp are equal so $v = 5$ V.

Apply KCL at the inverting input node of the op amp:

$$-\left(\frac{v_a-5}{10000}\right)-0.1\times10^{-3}-0=0 \quad \Rightarrow \quad v_a=4 \text{ V}$$

Apply Ohm's law to the 20 kΩ resistor

$$i = \frac{v_a}{20000} = \frac{1}{5}\text{mA}$$

(checked using LNAP 8/16/02)

P6.4-5


The voltages at the input nodes of an ideal op amp are equal so $v_a = 0$ V. Apply KCL at node *a*:

$$-\left(\frac{v_o-0}{3000}\right)-\left(\frac{12-0}{4000}\right)-2\cdot10^{-3}=0$$

$$\Rightarrow v_o = -15 \text{ V}$$

Apply KCL at the output node of the op amp:

$$i_o+\frac{v_o}{6000}+\frac{v_o}{3000}=0 \Rightarrow i_o=7.5 \text{ mA}$$




(checked using LNAP 8/16/02)

Download full file from answersun.com

https://answersun.com/download/solutions-manual-of-introduction-to-electric-circuits-by-dorf-svoboda-7th-edition/

P8.3-6

Before the switch opens, $v_o(t) = 5$ V $\Rightarrow v_o(0) = 5$ V. After the switch opens the part of the circuit connected to the capacitor can be replaced by it's Norton equivalent circuit to get:




Therefore $\tau = \dfrac{5}{20\times10^3} = 0.25$ ms.

Next, $i_L(t) = i_{sc} + (i_L(0) - i_{sc})\, e^{-\frac{t}{\tau}} = 0.5 - 0.25\, e^{-4000t}$ mA for $t > 0$

Finally, $v_o(t) = 5\dfrac{d}{dt} i_L(t) = 5\, e^{-4000t}$ V for $t > 0$


P8.3-7

At $t = 0^-$ (steady-state)



Since the input to this circuit is constant, the inductor will act like a short circuit when the circuit is at steady-state:

for t > 0




$$i_L(t) = i_L(0)\, e^{-(R/L)\,t} = 6\, e^{-20t} \text{ A}$$

Download full file from answersun.com

https://answersun.com/download/solutions-manual-of-introduction-to-electric-circuits-by-dorf-svoboda-7th-edition/

Section 11-10: The Ideal Transformer

P11.10-1



$$\mathbf{Z} = (2 + j3) + \frac{(100 - j75)}{5^2} = 6\ \Omega$$

$$\mathbf{I}_1 = \frac{12\angle 0°}{\mathbf{Z}} = \frac{12\angle 0°}{6} = 2\ \text{A}$$

$$\mathbf{V}_1 = \mathbf{I}_1\left(\frac{100 - j75}{n^2}\right) = (2)\left(\frac{100 - j75}{25}\right) = 10\angle -36.9°\ \text{V}$$

$$\mathbf{V}_2 = n\mathbf{V}_1 = 5\ (10\angle -36.9°) = 50\ \angle -36.9°\ \text{V}$$

$$\mathbf{I}_2 = \frac{\mathbf{I}_1}{n} = \frac{2}{5}\ \text{A}$$

P11.10-2

(a) $\mathbf{V}_0 = (5\times 10^{-3})(10{,}000) = 50\ \text{V}$

$$n = \frac{N_2}{N_1} = \frac{\mathbf{V}_0}{\mathbf{V}_1} = \frac{50}{10} = 5$$


(b) $$R_{ab} = \frac{1}{n^2} R_2 = \frac{1}{25}(10\times 10^3) = 400\ \Omega$$

(c) $$\mathbf{I}_s = \frac{10}{R_{ab}} = \frac{10}{400} = 0.025\ \text{A} = 25\ \text{mA}$$

Download full file from answersun.com

https://answersun.com/download/solutions-manual-of-introduction-to-electric-circuits-by-dorf-svoboda-7th-edition/

P15.8-6



Rather than find the Fourier Series of $v(t)$ directly, consider the signal $\hat{v}(t)$ shown above. These two signals are related by

$$v(t) = \hat{v}(t-1) - 6$$

since $v(t)$ is delayed by 1 ms and shifted down by 6 V.

The Fourier series of $\hat{v}(t)$ is obtained as follows:

$$T = 4\text{ ms} \quad \Rightarrow \quad \omega_0 = \frac{2\pi \text{ radians}}{4\text{ ms}} = \frac{\pi}{2}\text{ rad/ms}$$

$$\hat{a}_n = 0 \text{ because the average value of } \hat{v}(t) = 0$$

$$\hat{b}_n = \frac{1}{2}\int_0^4 (6-3t)\sin\left(n\frac{\pi}{2}t\right)dt \quad \text{because } \hat{v}(t) \text{ is an odd function.}$$

$$= 3\int_0^4 \sin\left(n\frac{\pi}{2}t\right)dt - \frac{3}{2}\int_0^4 t\sin\left(n\frac{\pi}{2}t\right)dt$$

$$= 3\frac{-\cos\left(n\frac{\pi}{2}t\right)}{n\frac{\pi}{2}}\Bigg|_0^4 - \frac{3}{2}\left[\left(\frac{1}{\frac{n^2\pi^2}{4}}\right)\sin\left(n\frac{\pi}{2}t\right) - \left(\frac{n\pi}{2}t\right)\cos\left(n\frac{\pi}{2}t\right)\right]_0^4$$

$$= \frac{6}{n\pi}\left(-1+\cos(2n\pi)\right) - \frac{6}{n^2\pi^2}\left(\left(\sin(2n\pi)-0\right) - \left(2n\pi - \cos(2\pi) - 0\right)\right) = \frac{12}{n\pi}$$

Finally,

$$\hat{v}(t) = \sum_{n=1}^{\infty}\frac{12}{n\pi}\sin n\frac{\pi}{2}t$$

The Fourier series of $v(t)$ is obtained from the Fourier series of $\hat{v}(t)$ as follows:

$$v(t) = -6 + \sum_{n=1}^{\infty}\frac{12}{n\pi}\sin n\frac{\pi}{2}(t-1) = -6 + \sum_{n=1}^{\infty}\frac{12}{n\pi}\sin\left(n\frac{\pi}{2}t - n\frac{\pi}{2}\right)$$

where t is in ms. Equivalently,

Download full file from answersun.com